



VG-8T socket - Screw terminal, wall/ Datasheet rail mount



Application

The VG-8T is a surface / wall and 35 mm rail mount relay socket. The VG-8T socket has one screw terminal per relay contact suitable for two wires up to 2.5 mm², so looping/daisy chaining can be done on the socket and no external connector or terminal is needed.

The VG-8T relay socket has no internal soldering connections which makes it highly reliable. A multifunction timer or diode module can be placed on the socket and is parallel connected with the relay coil. Refer to page 4 for ordering codes.

Description

The VG-8T relay socket is suitable for general purpose applications. Installation and replacement of relays is made easy and cost saving. No maintenance is required for the user.

Suitable for all G8-relays.

Features

- 35 mm rail mounting
- Screw terminals
- Suitable for G8-relays
- No internal soldering
- Retaining clip connection possible

Benefits

- Proven reliability
- Long term availability
- Easy to maintain
- Low life cycle cost

Industry compliancy

- IEC 60947-5-1 Electromechanical control circuit devices and switching elements
- IEC 61810 Electromechanical elementary relays
- IEC 60664-1 Insulation
- IEC 60529 Protection category
- UL
- CSA
- CE






VG-8T socket Technical specifications



Technical characteristics

Contact rating	12 A
Dielectric strength	IEC 60664-1, 250 V, 50/60 Hz, 1 min
Protecting category	IEC 60529, IP20
Mounting	35 mm rail mount
Ambient temperature	-25 °C+85 °C
Weight	52 g
Dimensions	75 x 38 x 26 mm
Wire size	$2 \times 2.5 \text{ mm}^2$
Wire stripping length	6.5 mm
Material	Polyester
Socket contacts	Screw terminal
Accessories	Various, see pages 4 & 5


Connection diagram





VG-8T socket Technical specifications

Dimensions







VG-8T socket Ordering codes

Ordering codes

Art. no.	Туре	Description
321000206	VG-8T	VG-8T socket for G8-relays

Socket accessories



CG-1

Art. no.	Туре	Description	Weight
321000203	CG-1	Relay retaining clip, metal	0.8 g





VG-8T socket Modules





T-21

Com-3TP

Art.no.	Туре	Voltage	Weight
321000208	Diode module with damping diode	6230 VDC	6.5 g
321000205	Multifunction timer module	24230 VDC	14 g
	8 time ranges (0.05 s 240 h) 8 different functions Function and time setting by dip-switch for fine tuning.		
8 different functionsFDelay - ONRDelay - OFF (+ control contact)WsOne shot - ON (+ control contact)WaOne shot - OFF (+ control contact)WuOne shot - ONEsDelay - ON (+ control contact)BpFlasher, starting OFFBiFlasher, starting ON			











Mors Smitt France SAS Tour Rosny 2, Avenue du Général de Gaulle, F - 93118 Rosny-sous-Bois Cedex, FRANCE T +33 (0)1 4812 1440, F +33 (0)1 4855 9001 E sales.msf@wabtec.com

Mors Smitt Asia Ltd. 29/F., Fun Towers, 35 Hung To Road Kwun Tong, Kowloon, HONG KONG SAR T +852 2343 5555, F +852 2343 6555 E sales.msa@wabtec.com

Mors Smitt B.V. Vrieslantlaan 6, 3526 AA Utrecht, NETHERLANDS T +31 (0)30 288 1311, F +31 (0)30 289 8816 E sales.msbv@wabtec.com

Mors Smitt Technologies Inc. 1010 Johnson Drive, Buffalo Grove, IL 60089-6918, USA T +1 847 777 6497, F +1 847 520 2222 E salesmst@wabtec.com

Mors Smitt UK Ltd.

Graycar Business Park, Barton under Needwood, Burton on Trent, Staffordshire, DE13 8EN, UK T +44 (0)1283 722 650 F +44 (0)1283 722 651 E sales.msuk@wabtec.com



(c) Copyright 2015

All rights reserved. Nothing from this edition may be multiplied, or made public in any form or manner, either electronically, mechanically, by photocopying, recording, or in any manner, without prior written consent from Mors Smitt. This also applies to accompanying drawings and diagrams. Due to a policy of continuous development Mors Smitt reserves the right to alter the equipment specification and description outlined in this datasheet without prior notice and no part of this publication shall be deemed to be part of any contract for the equipment unless specifically referred to as an inclusion within such contract. Mors Smitt does not warrant that any of the information contained herein is complete, accurate, free from potential errors, or fit for any particular purpose. Mors Smitt does not accept any responsibility arising from any party's use of the information in this document.